




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁵ : H03C 1/54, 1/60, 5/00	A1	(11) International Publication Number: WO 94/24759 (43) International Publication Date: 27 October 1994 (27.10.94)
(21) International Application Number: PCT/US94/04100 (22) International Filing Date: 14 April 1994 (14.04.94) (30) Priority Data: 08/045,790 14 April 1993 (14.04.93) US (71) Applicant: ACRODYNE INDUSTRIES, INC. [US/US]; 516 Township Lane Road, Blue Bell, PA 19422 (US). (72) Inventor: HULICK, Timothy, R.; 886 Brandon Lane, Schwenksville, PA 19473 (US). (74) Agents: MELSER, Allen, S. et al.; Mason, Fenwick & Lawrence, Suite 1000, 1225 Eye Street, N.W., Washington, DC 20005 (US).	(81) Designated States: AT, AU, BB, BG, BR, CA, CH, CN, CZ, DE, DK, ES, FI, GB, HU, JP, KP, KR, KZ, LK, LU, MG, MN, MW, NL, NO, NZ, PL, PT, RO, RU, SD, SE, SK, UA, European patent (AT, BE, CH, DE, DK, ES, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML, MR, NE, SN, TD, TG). Published <i>With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>	

(54) Title: BALANCED MODULATOR-TRANSMITTER



(57) Abstract

The invention provides a balanced modulator, which has at least one individual amplitude modulator (230) which does not provide a suppressed-carrier output. One example employs a single amplitude modulator (230) whose carrier input is selectively delayed a half wavelength by a delay element (260), depending on the output of a polarity detector (220), and whose amplitude input receives the absolute value of the modulated input signal. Quadrature amplitude modulation or single sideband modulation may be provided including the above modulator.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	GB	United Kingdom	MR	Mauritania
AU	Australia	GE	Georgia	MW	Malawi
BB	Barbados	GN	Guinea	NE	Niger
BE	Belgium	GR	Greece	NL	Netherlands
BF	Burkina Faso	HU	Hungary	NO	Norway
BG	Bulgaria	IE	Ireland	NZ	New Zealand
BJ	Benin	IT	Italy	PL	Poland
BR	Brazil	JP	Japan	PT	Portugal
BY	Belarus	KE	Kenya	RO	Romania
CA	Canada	KG	Kyrgyzstan	RU	Russian Federation
CF	Central African Republic	KP	Democratic People's Republic of Korea	SD	Sudan
CG	Congo	KR	Republic of Korea	SE	Sweden
CH	Switzerland	KZ	Kazakhstan	SI	Slovenia
CI	Côte d'Ivoire	LI	Liechtenstein	SK	Slovakia
CM	Cameroon	LK	Sri Lanka	SN	Senegal
CN	China	LU	Luxembourg	TD	Chad
CS	Czechoslovakia	LV	Latvia	TG	Togo
CZ	Czech Republic	MC	Monaco	TJ	Tajikistan
DE	Germany	MD	Republic of Moldova	TT	Trinidad and Tobago
DK	Denmark	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	US	United States of America
FI	Finland	MN	Mongolia	UZ	Uzbekistan
FR	France			VN	Viet Nam
GA	Gabon				

BALANCED MODULATOR-TRANSMITTER

CROSS-REFERENCE TO RELATED APPLICATIONS

The present patent application has the same Assignee as U.S. Patent Application Serial No. 07/924,525, filed August 4, 1992, and is related to U.S. Patent No. 4,804,931, issued February 14, 1989. Both documents are incorporated herein by reference.

BACKGROUND OF THE INVENTION1. Technical Field

The present invention relates to modulators. More specifically, the invention relates to balanced modulators (those having no carrier component in the output waveform), especially balanced quadrature amplitude modulation (QAM) modulators.

2. Background Art

In U.S. Patent No. 4,804,931 (which is incorporated herein by reference in its entirety), a digital amplitude modulator-transmitter is described. An amplitude modulator-transmitter embodying the teachings of the '931 patent is illustrated in FIG. 1.

The amplitude modulator 30 includes a predetermined number of quadrature hybrid power devices 32₁-32_n. The quadrature hybrid power devices 32₁-32_n are configured as combiners, and are arranged in cascade so that the output of one combiner is the first of two inputs of a successive combiner. In the exemplary illustration of FIG. 1, only four combiners are shown for ease of understanding.

The construction and operation of a quadrature hybrid device is described in detail in the '931 patent, and need not be described here. However, for purposes of the present discussion, a quadrature hybrid combiner may be implemented as a four-port device having first and second inputs, one output, and one isolated port. The first and second inputs receive two signals of a given amplitude that are 90° apart in phase. The input signals are combined to provide an output signal having an amplitude that is the sum of the amplitudes of the input signals. As shown in FIG. 1, ports 1 and 4

represent the first and second input ports. Port 3 represents an isolation port to which is attached a resistor representing a dummy load 34. Finally, port 2 defines the output port of each of the combiners.

5 An analog signal source 36, such as a microphone or a video generator, produces an analog signal that passes through an analog-to-digital converter (A/D converter, or ADC) 38. The digital output of the A/D converter appears on data lines 40.

10 As an example, there are four data lines, so that data consists of four-bit words. However, it is contemplated that 12- or 16-bit words may be employed to improve the quality of the signals being transmitted. Further, it is contemplated that a digital input signal may be fed directly to gates 42 without the need for A/D converter 38, should the modulating
15 signal already exist in binary form.

 Each of the bits, from the least significant bit (LSB) to the most significant bit (MSB), controls a respective gate 42₁-42_n. Each of the gates is connected in series with a
20 corresponding amplifier 44₁-44_n. The series combinations receive an RF signal from an RF signal generator 46, and provide respective second inputs to the combiners.

 The output port of the LSB combiner 32₁ represents the least significant bit of the digital word describing the
25 instantaneous value of the signal to be modulated. The second input of the combiner 32₂, adjacent the LSB combiner 32₁, represents a value that is twice as significant as that of the second input of the LSB combiner 32₁. Similarly, the second
30 input of each successive combiner represents a value twice as significant as that input to the immediately preceding combiner.

 Thus, the output of each combiner represents a binary weighted power signal. In particular, the signal appearing at the output of the MSB combiner 42_n represents the sum of
35 the power signals fed into the various combiners. This output signal is fed for transmission to a load, typically an antenna with conventional filtering.

 The modulator-transmitter in the '931 patent has many advantages, such as its ability to provide pseudo-continuous
40 amplitude modulation at any modulation index between 0 and 1,

at any carrier frequency, using any one of the wide variety of classes of amplifiers. However, it is not a balanced modulator, as a carrier component is present in the output waveform. Thus (assuming a sinusoidal modulating signal of angular frequency ω_m), the digital amplitude-modulator described in the '931 patent provides an output signal which may be represented as:

$$s_{AM}(t) = A(1 + \cos \omega_m t)(\cos \omega_c t) \quad (1)$$

where:

- 10 $s_{AM}(t)$ is the output of the amplitude modulator;
A is a constant;
 ω_m is the modulating signal angular frequency;
 ω_c is the carrier signal angular frequency; and
t is the variable for time.

15 As will readily be appreciated by those skilled in the art in light of the '931 disclosure, a carrier frequency component, and symmetrical upper and lower sidebands, are present in the output signal.

For various reasons appreciated by those skilled in the art, suppression of the carrier is often desirable. In particular, in formats which may be used for high definition television (HDTV) and digital cellular telephone systems, suppression of the carrier is required.

Generally, a balanced modulator provides an output having no carrier, and may be expressed by the formula:

$$s_{BAL}(t) = A(\cos \omega_m t)(\cos \omega_c t) \quad (2)$$

This formula assumes that the modulating waveform is sinusoidal in form with an angular frequency of ω_m . More generally, a balanced modulator receiving an arbitrary modulating waveform $a(t)$ having no DC component provides an output that can be described by the formula:

$$s_{BAL}(t) = A(a(t)) \cos \omega_c t \quad (3)$$

However, the '931 patent does not describe a manner in which a balanced modulator may be implemented. It is to meet this need that the present invention is directed.

Various patents are directed to modulators. For example, U.S. Patent No. 5,153,536 (Muller) discloses a QAM modulator having an arrangement of double modulators and partial modulators. U.S. Patent No. 3,757,222 (Oberbury) discloses a single sideband generator involving selective switching of

transmission line links. U.S. Patent No. 4,635,004 (Ishigaki) discloses a single sideband generator in which quarter-wave-shifted signals are alternately input to a balanced modulator. U.S. Patent No. 4,717,894 (Edwards et al.) discloses a method of calibrating a vector modulator involving in-phase and quadrature components. Finally, U.S. Patent No. 4,068,100 (Thompson) discloses an AM stereo system in which opposite-polarity half-cycles of a carrier are separately modulated with a different channel. However, none of the existing art is believed to provide all the advantages of the present invention.

DISCLOSURE OF THE INVENTION

The invention provides various embodiments of a balanced modulator, each of which involves one or more individual amplitude modulators which, individually, do not provide suppressed-carrier outputs. A first embodiment employs a single amplitude modulator whose carrier input is selectively delayed by a half wavelength, depending on the polarity of the input modulating signal, and whose amplitude input receives the absolute value of the modulating input signal. A second embodiment involves summation of the outputs of two amplitude modulators whose carrier inputs are responsive to carrier signals offset by a half carrier wavelength and whose modulating signal inputs are responsive only to signals of respectively opposite polarity. Further, quadrature amplitude modulation (QAM) modulators are provided by a combination of the above-described modulators. Moreover, another embodiment of the QAM modulator involves use of an amplitude modulator operating on polar coordinate representations of the input modulating signal. The invention is useful in single sideband modulation, up-conversion, down-conversion, synchronous detection, product detection and the like.

BRIEF DESCRIPTION OF DRAWINGS

The invention is better understood by reading the following Detailed Description of the Preferred Embodiments with reference to the accompanying drawing figures, in which like reference numerals refer to like elements throughout, and in which:

FIG. 1 illustrates an amplitude modulator constructed in accordance with the teachings of U.S. Patent No. 4,804,931.

FIG. 2 illustrates a first embodiment of the balanced modulator according to the present invention.

5 FIG. 3 illustrates a second embodiment of the balanced modulator according to the present invention.

FIGS. 4A and 4B illustrate quadrature amplitude modulators employing balanced modulators according to the embodiments of FIGS. 2 and 3, respectively.

10 FIG. 5 illustrates a further embodiment of a quadrature amplitude modulator according to the present invention.

FIG. 6 illustrates an exemplary single sideband modulator employing balanced modulators according to the present invention.

15 FIG. 7 illustrates an exemplary single sideband quadrature amplitude modulator according to the present invention.

BEST MODES FOR CARRYING OUT THE INVENTION

20 In describing preferred embodiments of the present invention illustrated in the drawings, specific terminology is employed for the sake of clarity. However, the invention is not intended to be limited to the specific terminology so selected, and it is to be understood that each specific
25 element includes all technical equivalents which operate in a similar manner to accomplish a similar purpose.

Referring now to FIG. 2, a first balanced modulator according to the present invention is illustrated. The input modulating waveform $a(t)$ is input to the modulator on
30 path 200. Path 200 leads to an absolute value functional block 210 and a polarity detector 220. The absolute value functional block 210 provides the instantaneous absolute value of $a(t)$ to the modulating data input of a digital amplitude modulator 230. Preferably, the modulator 230 is implemented
35 as the digital amplitude modulator described in the U.S. Patent No. 4,804,931, described above, with reference to FIG. 1. Modulator 230 provides an output of the type described above, in Formula 3.

Polarity detector 220 provides a binary output, depending
40 on the polarity of the input modulating signal $a(t)$. The

binary output of polarity detector 220 is input to the control input of a switch arrangement 250. The switch arrangement 250 receives a single input, from a carrier generator 240 which produces a signal $A \cos \omega_c t$. The switch arrangement 250 provides a carrier output to modulator 230.

Referring briefly to FIG. 1, it is understood that the data input to modulator 230 (FIG. 2) corresponds to the signal between elements 36, 38, and that the carrier input from switch arrangement 250 (FIG. 2) corresponds to RF signal generator 46 (FIG. 1).

Referring more specifically to the details of elements within FIG. 2, polarity detector 220 may be implemented through use of a voltage comparator having a non-inverting input and an inverting input. The modulating input signal $a(t)$ is provided to the non-inverting input, and the inverting input is connected to ground. The comparator's binary output is a first logic state (for example, 1) when $a(t)$ is greater than zero, and the output is a second value (for example, 0) when $a(t)$ is less than zero volts.

Switching arrangement 250 may be implemented as a double pole, double throw switch implemented using gallium arsenide (GaAs) switches which selectively connect, or disconnect, a delay element 260. This delay element may be in the form of a transmission line equal to half the wavelength of the carrier wave. In the illustrated example, when the output of polarity detector 220 is zero, the switches in switch arrangement 250 are connected in the manner illustrated, so as to bypass the half-wavelength delay element 260. Conversely, when polarity detector 220 outputs a 1, the switches connect the opposite poles, so that the half-wavelength delay line 260 is interposed between carrier generator 240 and modulator 230.

Finally, the absolute value function 210 may be implemented according to any suitable configuration, as readily appreciated by those skilled in the art. For example, it may be implemented using a precision full wave rectifier.

The elements in FIG. 2 may be implemented differently than as specifically described above, while still remaining within the scope of the present invention. In any event, the

modulator of FIG. 2 provides a double sideband suppressed carrier modulation output.

5 A second embodiment according to the present invention is shown in FIG. 3. The FIG. 3 embodiment employs a duplicate modulator instead of employing a switching arrangement such as that in the FIG. 2 embodiment.

10 Referring to FIG. 3, the input modulating signal $a(t)$ is input to schematically illustrated clipping circuits 310, 320. Clipping circuit 310 provides an output only when $a(t)$ is greater than zero. Conversely, clipping circuit 320 provides an output only when $a(t)$ is less than zero. Clipping circuits 310, 320 provide their outputs to respective modulators 330₁, 330₂. Preferably, these modulators are implemented as the digital amplitude modulator disclosed in U.S. Patent No. 15 4,804,931, described with reference to FIG. 1. It is understood that the modulating inputs to the FIG. 3 modulators correspond to the signal between elements 36, 38 in FIG. 1.

20 Referring again to FIG. 3, a carrier generator 340 is provided, connected to a half-wavelength delay element 360. First modulator 330₁ receives the output of carrier generator 340 directly, whereas second modulator 330₂ receives the half-wavelength delayed carrier from delay element 360. It is understood that the carrier inputs in the FIG. 3 modulators correspond to the RF signal generator 46 (FIG. 1).

25 Modulators 330₁ and 330₂ provide respective outputs to a summing element (adder) 370, whose output may be expressed as the generalized balanced modulator Formula 3, provided above. Adder 370 adds the outputs of the two modulators, but it is recognized that, at any given instant, at least one of the 30 modulators will have zero output due to the operation of clipping circuits 310, 320. By implication, the ultimate output of the system, $s(t)$, is the output of the one modulator which is active at any given instant.

35 The illustration of clipper elements 310, 320 is schematic in nature, and is used for purposes of explanation. In a practical embodiment, each modulator 330₁, 330₂ would have its own analog-to-digital converter (ADC) at its input. The first modulator's ADC (element 38 in FIG. 1) is configured to respond with measurable (non-zero) output only when its 40 input is greater than zero. Conversely, the second

modulator's ADC provides non-zero output only when the modulating input wave form $a(t)$ is less than zero. In this manner, actual analog clipping elements 310, 320 are avoided.

As described in the '930 patent, each of the individual
5 modulators 230, 330₁, 330₂ (FIGS. 2-3) may take advantage of the high efficiency of non-linear RF amplifiers while still providing a linear amplitude-modulated signal at signal levels high enough for transmission. The present invention builds on the advantages of that modulator by exploiting its
10 efficiency and high signal levels. Moreover, present invention provides apparatus for suppressed-carrier modulation and transmission which is especially suitable for various standardized transmission formats. A notable example is quadrature amplitude modulation (QAM).

15 QAM modulators provide output in which two carriers, differing in phase by one-quarter wavelength, are suppressed. Usually, the modulating signal input to QAM modulators include a series of pairs of pulses, with the average DC value of each pair of pulses being zero. Advantageously, the present
20 invention provides a QAM modulator which can modulate any arbitrary input waveform having no DC component, even those not of the paired pulse standard.

FIGS. 4A and 4B show QAM modulators employing the teachings of the embodiments of FIGS. 2 and 3. The input
25 modulating signal is provided in the form of in-phase and quadrature components $a_i(t)$ and $a_q(t)$, respectively. These in-phase and quadrature signals are input to the modulating inputs of respective modulators 420, 430. In FIG. 4A, the modulators 420, 430 are indicated as being of the type shown
30 in FIG. 2 (excepting the carrier generator). Similarly, FIG. 4B indicates the modulators 420, 430 being of the type shown in FIG. 3 (again, excepting the carrier generator).

The modulators 420, 430 receive their respective carrier inputs from a carrier generator 440 and from a quarter-wave delay element 460. The modulators 420, 430 provide outputs
35 to a summing device 470. Summing device 470 provides the QAM modulated output signal.

The QAM output signal may be of the form described by the following formula:

$$S_{QAM}(t) = A[a_I(t) \cos \omega_c t + a_Q(t) \sin \omega_c t] \quad (4)$$

where:

5 A is a constant;

$a_I(t)$ is the in-phase component of the modulating signal;

$a_Q(t)$ is the quadrature component of the modulating signal;

$a(t)$ equals $a_I(t)$ plus $a_Q(t)$;

10 ω_c is the carrier angular frequency;

 t is the variable for time; and

$a_I(t)$ and $a_Q(t)$ can take on positive or negative values.

15 Referring now to FIG. 5, still another quadrature amplitude modulator according to the present invention is illustrated. The invention of FIG. 5 builds on the advantages of the embodiments of FIGS. 2-4, and provides additional benefits relating to power savings and lower required Nyquist sampling rates.

20 The embodiment of FIG. 5 avoids use of the combiners (summing devices) 370 in FIG. 3 (which dissipate half the power from the individual digital amplitude modulators 330₁, 330₂ when the combiner's input signals are not coherent in phase and amplitude). In the case of quadrature amplitude modulation, this lack of coherence is always the case because
25 $a_I(t)$ and $a_Q(t)$ are independent of each other. Also, because of the manner in which the in-phase and quadrature components are summed, there is a discontinuity in the waveform at the crossover point. This discontinuity introduces energy at high
30 frequencies, necessitating use of gated Class C amplifiers to fulfill higher Nyquist sampling rate requirements.

35 The embodiment of FIG. 5 takes advantage of a polar coordinate representation of the input modulating signal, as opposed to the rectangular coordinate representation used in the foregoing embodiments. As shown in FIG. 5, a rectangular to polar converter 520 receives an input modulating signal in the form of in-phase and quadrature signal components. Converter 520 provides magnitude and phase output signals. The magnitude and phase output signals are of the form:

40

$$R(t) = \sqrt{[a_I(t)]^2 + [a_Q(t)]^2} \quad (5)$$

$$\theta(t) = \arctan\left(\frac{a_Q(t)}{a_I(t)}\right) \quad (6)$$

These respective amplitude and phase representations indicate a polar coordinate representation of the modulating signal which is expressed as:

$$S(t) = R(t) e^{j\theta(t)} \quad (7)$$

5 The FIG. 5 embodiment is also provided with a carrier generator 540 which is substantially the same as carrier generators in previously described embodiments. A phase modulator 550 receives the output of the carrier generator 540 as a signal input. Phase modulator 550 also receives the
10 phase representation of the input modulating signal $\theta(t)$ as a phase modulating input. Phase modulator 550 thus modulates the carrier from carrier generator 540 in accordance with the phase of the modulating input signal, providing the phase-modulated carrier to the carrier input of amplitude
15 modulator 530.

 Amplitude modulator 530 is preferably implemented in accordance with the teachings of the '931 patent illustrated in FIG. 1. Converter 520 provides the amplitude $R(t)$ of the
20 modulating signal to the modulator's amplitude input. It is understood that the amplitude input corresponds to the signal between elements 36, 38 of FIG. 1, and that the carrier (here, phase) input corresponds to the RF signal generator 46 (FIG. 1).

25 Modulator 530 therefore provides a quadrature amplitude modulation output which provides the advantages of the FIG. 4A, 4B embodiments, but provides further advantages of increased power efficiency and lower Nyquist sampling rate requirements.

30 Referring now to FIG. 6, a further aspect of the present invention, a single sideband modulator, is illustrated.

 A baseband input modulating waveform, here shown as $\cos \omega_m t$, is shown entering a baseband quarter-wavelength phase

shifter 610 and the amplitude input of a balanced modulator 640. The output of phase shifter 610 is input to the amplitude input of a balanced modulator 630. The balanced modulators 630, 640 are preferably of the type described in the above embodiments.

Also illustrated in FIG. 6 is a carrier generator 620 which provides a carrier-frequency signal to the carrier input of balanced modulator 640 and to a carrier frequency quarter-wavelength phase shifter 650. Phase shifter 650 provides a phase-shifted carrier input to the balanced modulator 630. The respective outputs of balanced modulators 630, 640 are input to a summation device 660, preferably an in-phase power combiner. Summation device 660 provides the single sideband output.

As will be appreciated by those skilled in the art, the output of balanced modulator 630 may be expressed as:

$$\sin \omega_c t \sin \omega_m t = \frac{1}{2} \cos(\omega_c - \omega_m)t - \frac{1}{2} \cos(\omega_c + \omega_m)t \quad (8)$$

Similarly, the output of balanced modulator 640 may be expressed as:

$$\cos \omega_c t \cos \omega_m t = \frac{1}{2} \cos(\omega_c - \omega_m)t + \frac{1}{2} \cos(\omega_c + \omega_m)t \quad (9)$$

By implication, the single sideband output may be expressed as:

$$SSB = \cos(\omega_c - \omega_m)t \quad (10)$$

The illustrated device produces a lower sideband signal. However, by switching exactly one (not both) of the phase shifters 610, 650 onto the other side of its respective input node so that it directly feeds balanced modulator 640 instead of balanced modulator 630, an upper sideband SSB modulator is produced.

Referring now to FIG. 7, a single sideband quadrature amplitude modulator is illustrated. The FIG. 7 modulator closely resembles the single sideband modulator of FIG. 6. Baseband phase shifter 710, carrier generator 720, balanced modulators 730, 740, carrier frequency phase shifter 750, and summation device 760 may be implemented as corresponding FIG. 6 elements 610, 620, 630, 640, 650 and 660.

However, a phase modulator 770, operating in substantially the same manner as phase modulator 550 (FIG. 5), is inserted at the output of carrier generator 720. Moreover, to employ the advantages of the polar coordinate

representation of the input modulating signal, the inputs to the baseband phase shifter 710 and balanced modulator 740 is the modulating signal's magnitude $R(t)$, expressed in general form in Formula (5), above. Phase modulator 770 receives at its modulating input the phase function $\theta(t)$ expressed in Formula (6), above.

In operation, the modulating inputs of the balanced modulators 730, 740 receive respective signals which constitute the magnitude $R(t)$ of the input modulating signal, offset from each other by one-quarter baseband wavelength. The carrier inputs of the two balanced modulators 730, 740 receive respective carrier signals which have been offset from each other by one-quarter carrier wavelength, after being phase-modulated by the phase $\theta(t)$ of the input modulating signal. The outputs of the balanced modulators 730, 740 are summed by element 760, to provide the single sideband, quadrature amplitude modulation output signal. The FIG. 7 single sideband, quadrature amplitude modulator may be considered to combine the advantages of the FIG. 5 QAM modulator and the FIG. 6 SSB modulator.

It will be appreciated that the various combining (summation) devices in the illustrated embodiments may be implemented in various ways. For example, ninety degree hybrid combiners such as those described in the '931 patent may be employed, as they provide proper isolation of the inputs while minimizing wasted power. However, other combining (summation) devices may be employed, such as in-phase Wilkinson combiners and branch combiners, based on their suitability to a particular implementation.

In addition to the illustrated uses of the present invention, the balanced modulators may readily be used for up conversion, down conversion, synchronous detection, product detection, and other known uses of mixers.

Modifications and variations of the above-described embodiments of the present invention are possible, as appreciated by those skilled in the art in light of the above teachings. It is therefore to be understood that, within the scope of the appended claims and their equivalents, the invention may be practiced otherwise than as specifically described.

WHAT IS CLAIMED IS:

1. A balanced modulator for modulating an input modulating signal and for providing an output modulated signal, the balanced modulator comprising:

5 a) an amplitude modulator having an amplitude input and a carrier input, the amplitude modulator providing the modulated output of the balanced modulator;

10 b) means for providing an absolute value of the input modulating signal to the amplitude input of the amplitude modulator;

c) a carrier generator; and

15 d) means for selectively inserting or removing a half-wavelength delay into an output of the carrier generator in accordance with a polarity of the input modulating signal, and for providing a resulting carrier signal to the carrier input of the amplitude modulator.

2. The balanced modulator of claim 1, wherein the amplitude modulator includes:

20 a) a plurality of component signal generation devices, responsive to the amplitude input and to the carrier input and outputting a corresponding plurality of component signals, wherein:

25 1) each component signal output has a strength that is a predetermined multiple of a strength of a component signal of a preceding component signal generation device; and

2) the modulator's amplitude input controls the magnitude of the plurality of component signals; and

30 b) a plurality of combiners arranged in cascade, each combiner being connected to a respective component signal generation device, wherein:

35 1) each combiner after a first combiner combines (i) a combiner output from a previous combiner and (ii) the component signal output from its respective component signal generation device; and

2) a last combiner provides a modulator output signal indicative of a sum of the component signals.

3. A balanced modulator for modulating an input modulating signal and for providing an output modulated signal, the balanced modulator comprising:

5 a carrier generator for generating a first carrier signal;

a half-wavelength delay element for delaying the first carrier signal and providing a resultant inverted carrier signal;

10 a first amplitude modulator, responsive to the input modulating signal when it is greater than zero, and to the first carrier signal, for producing a first modulator output signal;

15 a second amplitude modulator, responsive to the input modulating signal when it is less than zero, and to the inverted carrier signal, for producing a second modulator output signal; and

20 a combining element, responsive to the first and second modulator output signals, the combining element providing the modulated output signal of the balanced modulator.

4. The balanced modulator of claim 3, wherein each of the first and second amplitude modulators includes:

25 a) an amplitude input;
b) a carrier input;
c) a plurality of component signal generation devices, responsive to the amplitude input and to the carrier input and outputting a corresponding plurality of component signals, wherein:

30 1) each component signal output has a strength that is a predetermined multiple of a strength of a component signal of a preceding component signal generation device; and

35 2) the modulator's amplitude input controls the magnitude of the plurality of component signals; and

d) a plurality of combiners arranged in cascade, each combiner being connected to a respective component signal generation device, wherein:

40 1) each combiner after a first combiner combines (i) a combiner output from a previous combiner

and (ii) the component signal output from its respective component signal generation device; and

2) a last combiner provides a modulator output signal indicative of a sum of the component signals.

5
5. A quadrature amplitude modulator for receiving an input modulating signal and providing a QAM output signal, the modulator comprising:

10 a carrier generator providing a first carrier signal;

means for providing a second carrier signal delayed by a quarter-wavelength compared to the first carrier signal;

15 a first balanced modulator having an amplitude input responsive to an in-phase component of the input modulating signal and a carrier input responsive to the first carrier signal;

20 a second balanced modulator having an amplitude input responsive to a quadrature component of the input modulating signal and a carrier input responsive to the second carrier signal; and

25 a combining element, responsive to outputs from the first and second modulators, the combining element providing the QAM output signal.

6. The quadrature amplitude modulator of claim 5, wherein at least one of the first or second balanced modulator includes:

30 a) an amplitude modulator having an amplitude input and a carrier input, the amplitude modulator providing the modulated output of the balanced modulator;

b) means for providing an absolute value of one of the in-phase or quadrature signals to the amplitude input of the amplitude modulator; and

35 c) means for selectively inserting or removing a half-wavelength delay into one of the first or second carrier signals in accordance with a polarity of the input modulating signal, and for providing a resulting carrier signal to the carrier input of the amplitude modulator.

40

7. The quadrature amplitude modulator of claim 6, wherein the amplitude modulator includes:

5 a) a plurality of component signal generation devices, responsive to the amplitude input and to the carrier input and outputting a corresponding plurality of component signals, wherein:

10 1) each component signal output has a strength that is a predetermined multiple of a strength of a component signal of a preceding component signal generation device; and

2) the modulator's amplitude input controls the magnitude of the plurality of component signals; and

15 b) a plurality of combiners arranged in cascade, each combiner being connected to a respective component signal generation device, wherein:

1) each combiner after a first combiner combines (i) a combiner output from a previous combiner and (ii) the component signal output from its respective component signal generation device; and

20 2) a last combiner provides a modulator output signal indicative of a sum of the component signals.

8. The quadrature amplitude modulator of claim 5, wherein at least one of the first or second balanced modulator includes:

a half-wavelength delay element for delaying the first or second carrier signal and providing a resultant inverted carrier signal;

30 a first amplitude modulator, responsive to one of the in-phase or quadrature signals when it is greater than zero, and to the first or second carrier signal, for producing a first modulator output signal;

35 a second amplitude modulator, responsive to one of the in-phase or quadrature signals when it is less than zero, and to the inverted carrier signal, for producing a second modulator output signal; and

a combining element, responsive to the first and second modulator output signals, the combining element

providing the modulated output signal of the balanced modulator.

9. The quadrature amplitude modulator of claim 8, wherein each of the first and second amplitude modulators includes:

a) an amplitude input;
b) a carrier input;
c) a plurality of component signal generation devices, responsive to the amplitude input and to the carrier input and outputting a corresponding plurality of component signals, wherein:

1) each component signal output has a strength that is a predetermined multiple of a strength of a component signal of a preceding component signal generation device; and

2) the modulator's amplitude input controls the magnitude of the plurality of component signals; and

d) a plurality of combiners arranged in cascade, each combiner being connected to a respective component signal generation device, wherein:

1) each combiner after a first combiner combines (i) a combiner output from a previous combiner and (ii) the component signal output from its respective component signal generation device; and

2) a last combiner provides a modulator output signal indicative of a sum of the component signals.

10. A quadrature amplitude modulator for modulating an input modulating signal and providing a QAM output signal, the modulator comprising:

an amplitude modulator having an amplitude input responsive to a magnitude of the input modulating signal, and a carrier input, the modulator providing the QAM output signal;

a carrier generator having a first carrier output signal; and

a phase modulator having a carrier input responsive to the first carrier signal and a phase modulating input

responsive to a phase signal indicative of the phase of the input modulating signal to the balanced modulator, the phase modulator having an output carrier signal which constitutes the first carrier signal shifted in phase in accordance with the phase modulator's phase modulating input signal, the phase modulator's output being provided to the carrier input of the amplitude modulator.

11. The quadrature amplitude modulator of claim 10, wherein the amplitude modulator includes:

a) a plurality of component signal generation devices, responsive to the amplitude input and to the carrier input and outputting a corresponding plurality of component signals, wherein:

1) each component signal output has a strength that is a predetermined multiple of a strength of a component signal of a preceding component signal generation device; and

2) the modulator's amplitude input controls the magnitude of the plurality of component signals; and

b) a plurality of combiners arranged in cascade, each combiner being connected to a respective component signal generation device, wherein:

1) each combiner after a first combiner combines (i) a combiner output from a previous combiner and (ii) the component signal output from its respective component signal generation device; and

2) a last combiner provides a modulator output signal indicative of a sum of the component signals.

12. A single sideband modulator for modulating a baseband input modulating signal and for generating a single sideband output signal, the modulator comprising:

a) means for providing first and second baseband signals offset by one-quarter of a baseband wavelength;

b) means for providing first and second carrier signals offset by one-quarter of a carrier frequency wavelength;

c) first and second balanced modulators, receiving the first baseband and carrier signals, and second baseband and carrier signals, respectively; and

5 d) a combining device, responsive to outputs of the first and second balanced modulators, the combining device providing the single sideband output signal;

wherein at least one of the first or second balanced modulators includes:

10 1) an amplitude modulator having an amplitude input and a carrier input, the amplitude modulator providing the modulated output of the balanced modulator;

15 2) means for providing an absolute value of one of the first or second baseband signals to the amplitude input of the amplitude modulator; and

20 3) means for selectively inserting or removing a half-wavelength delay into one of the first or second carrier signals in accordance with a polarity of the one of the first or second baseband signals, and for providing a resulting carrier signal to the carrier input of the amplitude modulator.

13. The single sideband modulator of claim 12, wherein the amplitude modulator includes:

25 a) a plurality of component signal generation devices, responsive to the amplitude input and to the carrier input and outputting a corresponding plurality of component signals, wherein:

30 1) each component signal output has a strength that is a predetermined multiple of a strength of a component signal of a preceding component signal generation device; and

2) the modulator's amplitude input controls the magnitude of the plurality of component signals; and

35 b) a plurality of combiners arranged in cascade, each combiner being connected to a respective component signal generation device, wherein:

1) each combiner after a first combiner combines (i) a combiner output from a previous combiner

and (ii) the component signal output from its respective component signal generation device; and

2) a last combiner provides a modulator output signal indicative of a sum of the component signals.

14. A single sideband modulator for modulating a baseband input modulating signal and for generating a single sideband output signal, the modulator comprising:

a) means for providing first and second baseband signals offset by one-quarter of a baseband wavelength;

b) means for providing first and second carrier signals offset by one-quarter of a carrier frequency wavelength;

c) first and second balanced modulators, receiving the first baseband and carrier signals, and second baseband and carrier signals, respectively; and

d) a combining device, responsive to outputs of the first and second balanced modulators, the combining device providing the single sideband output signal;

wherein at least one of the first or second balanced modulators includes:

1) a half-wavelength delay element for delaying the first or second carrier signal and providing a resultant inverted carrier signal;

2) a first amplitude modulator, responsive to one of the first or second baseband signals when it is greater than zero, and to the first or second carrier signal, for producing a first modulator output signal;

3) a second amplitude modulator, responsive to the one of the first or second baseband signals when it is less than zero, and to the inverted carrier signal, for producing a second modulator output signal; and

4) a combining element, responsive to the first and second modulator output signals, the combining element providing the modulated output signal of the balanced modulator.

15. The single sideband modulator of claim 14, wherein each of the first and second amplitude modulators includes:

a) an amplitude input;
b) a carrier input;
5 c) a plurality of component signal generation devices, responsive to the amplitude input and to the carrier input and outputting a corresponding plurality of component signals, wherein:

1) each component signal output has a
10 strength that is a predetermined multiple of a strength of a component signal of a preceding component signal generation device; and

2) the modulator's amplitude input controls the magnitude of the plurality of component signals; and

15 d) a plurality of combiners arranged in cascade, each combiner being connected to a respective component signal generation device, wherein:

1) each combiner after a first combiner
20 combines (i) a combiner output from a previous combiner and (ii) the component signal output from its respective component signal generation device; and

2) a last combiner provides a modulator
output signal indicative of a sum of the component signals.

25

16. A single sideband, quadrature amplitude modulator for modulating an input modulating signal and providing an SSB, QAM output signal, the modulator comprising:

30 a) means for receiving a polar coordinate amplitude signal indicative of the amplitude of the input modulating signal and for providing first and second polar amplitude signals offset from each other by one-quarter of a baseband wavelength;

35 b) a carrier generator providing a first carrier output signal;

c) a phase modulator having a carrier input responsive to the first carrier signal and a phase modulating input responsive to a polar phase signal indicative of the phase of the input modulating signal, the phase modulator
40 having a phase modulator output carrier signal which

constitutes the first carrier signal shifted in phase in accordance with the polar phase signal;

5 d) means for providing first and second phase-modulated carrier signals offset by one-quarter of a carrier frequency wavelength, the first and second phase-modulated carrier signals being derived from the phase modulator output carrier signal;

10 e) first and second balanced modulators, receiving the first polar amplitude and phase-modulated carrier signals, and the second polar amplitude and phase-modulated carrier signals, respectively; and

f) a combining device, responsive to outputs of the first and second balanced modulators, the combining device providing the single sideband output signal.

15

17. The single sideband, quadrature amplitude modulator of claim 16, wherein at least one of the first or second balanced modulators includes:

20 a) an amplitude modulator having an amplitude input and a carrier input, the amplitude modulator providing a modulated output of the balanced modulator;

b) means for providing an absolute value of one of the polar amplitude inputs to the amplitude input of the amplitude modulator; and

25 c) means for selectively inserting or removing a half-wavelength delay into one of the phase-modulated carrier signals in accordance with a polarity of the polar amplitude input, and for providing a resulting carrier signal to the carrier input of the amplitude modulator.

30

18. The single sideband, quadrature amplitude modulator of claim 16, wherein at least one of the first or second balanced modulators includes:

35 a half-wavelength delay element for delaying the phase-modulated carrier signal and providing a resultant inverted carrier signal;

40 a first amplitude modulator, responsive to the polar amplitude signal when it is greater than zero, and to the phase-modulated carrier signal, for producing a first modulator output signal;

a second amplitude modulator, responsive to the polar amplitude signal when it is less than zero, and to the inverted carrier signal, for producing a second modulator output signal; and

- 5 a combining element, responsive to the first and second modulator output signals, the combining element providing the balanced modulator output signal.




FIG. 1




FIG. 2




FIG. 3




FIG. 4A




FIG. 4B




FIG. 5




FIG. 6




FIG. 7

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US94/04100

A. CLASSIFICATION OF SUBJECT MATTER

IPC(5) : H03C 1/54, 1/60, 5/00

US CL : 332/103, 167, 170

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 332/103, 167, 170, 168, 169, 171, 104, 105; 455/46, 47, 109

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US, A, 3,243,731 (ERICKSON) 29 March 1966, column 2, line 63 to column 3, line 19.	5
X	US, A, 3,054,073 (POWERS) 11 September 1962, column 3, line 64 to column 5, line 64.	10
--		----
Y		11
Y	US, A, 4,804,931 (HULICK) 14 February 1989, column 4, lines 50-60 and column 5, lines 4-27.	11
A	US, A, 3,496,491 (KRAUSE) 17 February 1970, column 2, lines 1-23.	3
A	US, A, 4,726,039 (PIESINGER) 16 February 1988, column 5, lines 6-21.	3

☐ Further documents are listed in the continuation of Box C. ☐ See patent family annex.

* Special categories of cited documents:	"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
"A" document defining the general state of the art which is not considered to be of particular relevance	"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
"E" earlier document published on or after the international filing date	"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	"Z" document member of the same patent family
"O" document referring to an oral disclosure, use, exhibition or other means	
"P" document published prior to the international filing date but later than the priority date claimed	

Date of the actual completion of the international search

17 AUGUST 1994

Date of mailing of the international search report

AUG 29 1994

Name and mailing address of the ISA/US
Commissioner of Patents and Trademarks
Box PCT
Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

DOLINAR, ANDREW M. *Andrew M. Dolinar*

Telephone No. (703) 308-1948